<text>

The **Quad Joystick** is a 4 camera controller useful where space is at a premium. The LCD display and the associated controls offer access to the majority of remote camera functions.

The controller is constructed from an aluminium extrusion with fully machined end plates which incorporate the input/output socket and the focus control. Rubber inserts on the end plates and soft touch knobs give a comfortable feel to the controller and offer good grip on hard surfaces.

Primary Functions

The main functions are accessed directly via the dedicated knobs and buttons. The LCD display will show the iris values as they are changed.

3 axis Joystick	Pan, Tilt & Zoom
End Wheel	Focus
Knob	Iris
Touch Down	Iris Auto/Manual
Button	Record / Stop
4 x Buttons	Camera Select 1-4

All other functions are accessed via the mini LCD display using the associated knob and the associated button.

Menu Functions

Master Gain Shutter Speed White Balance - (manual, auto, preset, etc.) **Red Gain** Blue Gain Gamma Detail **Master Pedestal** Iris Range Pan Speed Tilt Speed **Reverse Pan/Tilt** Zoom Reverse **Focus Reverse** Change Head ID Reset ALL to #1 **Store Preset** Goto Preset Infra Red Mode Output Standard - (1080i/50,1080i/60, 720p/50, 720p/60, PAL 4:3/16:9, NTSC 4:3/16:9) Power Up Memory On/Clear **Digital Zoom On/Off** Zoom Limit On/Off **Remote Relay On/Off** Auto Focus On/Off **Roll Enable & Trim** Other functions added as required

RCP Input

A simple upgrade enables the **Quad Joystick** to accept remote data from any **BR-Remote** RCP. This requires a special cable and a code entry to activate the software. When ordering this at a later date you will need the serial number.

Specifications

Power:12v, 200mADimensions:W320mm, H70mm, D115mmOutput:XLR4 - RS485Input (from RCP)XLR4 - RS485Max Cable Length:**1km**

BR -Remote Ltd

Units 14 - 20, Setley Ridge Vineyard Lymington Road Brockenhurst SO42 7UF UK.

br-remote.com

+44 (0)1590 622440